

20" Multi-Format LCD Monitor

DT-V20L3G

- 3G and Dual Link equipped SMPTE 424M/425M/372M
- JVC 10-bit video processing
- High operating viewing angle
- Waveform/Vector scope
- LTC & VITC support
- Gamma selection
- Various marker function
- Audio level meter up to 12ch



HIGHLIGHTS

3G/Dual Link Equipped

1080p uncompressed digital video data transmitted at a maximum rate of 60 frames per second at 3 GB/second can be input with one HD SDI Input. Dual Link is available through two HD SDI inputs.

■ IPS (In-Plane-Switching) LCD Panel

IPS panels with wide viewing angles and low chromatic variation ensure minimal colour change from different viewing positions.

Gamma Preset Mode

JVC offers various pre-set gamma modes (2.2, 2.35, 2.45, 2.6) to meet your application needs.

Vector Scope*

High-quality vector scope allows simple checking of hue and saturation of digital video signals. Hue and saturation of colour signal are detected and displayed as a vector with resolution of 254 x 254 Compatible with video, component, SDI (SD/HD), DVI



tion can be displaved when

Level A mapping structure 1 Level A mapping structure 2

Level A mapping structure 3

Level B data stream

Level B data stream 2 Level B DUAL LINK

Level A mapping structure 4

3G-SDI Input Format

ollowing sign 3G-SDI sian

3G A-1 3G A-2

3G A-3

3G A-4

3G B-DS

3G B-DS

Vector Scope

3G B-DUAL

178°

(except PC signals) input signals, and offers a double-size display^{**} option and selection of display position or translucence functions.

Waveform*

Detects video, component (except RGB), SDI, DVI (except PC) brightness signals and displays them with resolution of 360×254 for SD signals or resolution of 480×254 for HD signals. In addition, it is also



possible to perform checks at the colour signal level of each colour per screen for R/G/B, Y/PB/PR, Y/CB/CR. Over-level function enables peak brightness to be checked at a glance. The display allows a double-size display** option, and selection of display position or translucence functions.

Waveform

Advanced Audio Level Meter

The channel number is displayed in each level bar. In addition, you can check the status of the audio signal at a glance for Reference Level/Over Level 0 dB, three set levels, and peak hold function.



Audio Level Meter



*Two display sizes cannot be displayed at the same time. *The position is fixed for double-size display.

DT-V SERIES

20" Multi-Format LCD Monitor

HD/SD SDI

Gold-plated 3G/Dual link ready

DVI-D

Audio In/Out Speaker Stere0 RS-232C

RS-485 In/Out

Make/ trigger Vector scope

Waveform monitoring

Gamma preset Area marker

Safety marker

Tally lamp

Time code

CRC error

Audio level meter

Source ID display

1:1 mode

I/P mode

Stand

(Tilt & height adjustable)

VESA

Powe AC

Rear Panel

INALS TERM

INPUT

TROLS

<u>S</u>

FUNCTIONS

ATION

NSTAL

PERATION



Advanced 3G/Dual-link HD Monitor with Glare IPS Panel

Features

- 1680 x 1050 resolution
- Wide viewing angle 178°/178° with IPS panel
- 3G/dual link equipped
- Circuits that deliver low latency of less than one frame
- Waveform monitoring with over level function
- Vector scope with selectable size and position
- Advanced audio level meter up to 12 channels
- Exclusive JVC image processing technology
- LTC & VITC support
- Selectable gamma preset modes
- Wide selection of video production functions
- Easy-to-operate front panel controls
- Front LED dimmer function
- Source ID input by ASCII code
- (Red/Green/White colour linked with tally)
- Information position selectable
- 1:1 mode
- Gold-plated HD/SD SDI terminals with embedded audio
- DVI-D with HDCP terminal
- RS-232C, RS-485 remote
- Audio speaker built-in
- Rugged, adjustable stand provided

Input Format

VIDEO	Input terminals					
Signal name		COMPO. /RGB (Analogue	E. AUDIO SDI (IN 1, IN 2)*2			DVI-D (HDCP)(Digital
oigna namo	IN1, IN2	component/Analogue RGB)*1	SD/HD (1.5G)	3G SDI	DUAL LINK	component/digital RGB)
NTSC	1	—	-	-	-	—
PAL	1	_	_	_	_	_
BW(50Hz/60Hz)	1	_	-	-	-	-
480/59.94i, 60i	-	1	1	-	-	1
576/50i	-	1	1	-	-	1
480/59.94p, 60p	-	1	-	-	-	1
576/50p	-	1	-	-	-	1
640 x 480/59.94p, 60p	-	_	_	-	-	1
720/23.98p, 24p, 25p, 29.97p, 30p	-	1	1	1	-	-
720/50p, 59.94p, 60p	-	1	1	1	-	1
1080/50i, 59.94i, 60i	-	1	1	1	1	1
1080/50p, 59.94p, 60p	-	—	-	1	1	1
1035/59.94i*4, 60i*3	-	√ *3*4	1	-	-	√ *3*4
1080/23.98p, 24p, 25p, 29.97p, 30p	-	1	1	1	1	1
1080/23.98psf, 24psf, 29.97psf*4, 30psf*3	-	√ *3*4	√ *3*4	1	1	_
1080/25psf	-	_	-	1	1	_

***: Analogue component/analogue RGB signals are compatible with G on sync signal, Y on sync signals, and composite sy signals (CS). The separate sync signal (RS/VS) is not compatible.
**: Compatible with EMBEDDEC AUDIO signals.
*3: The signal is necognized as 1080/60, and the status is displayed as *1080/60.*
*1: The signal is necognized as 1080/59.44, and the status is displayed as *1080/59.94,.*

Model		DT-V20L3G			
Туре		Multi format LCD monitor			
Screen Size		Type 20 wide format			
Aspect Ratio		16:10			
LCD Panel		20" wide, active matrix TFT			
Effective Screen Size (W x	H)	433.4 x 270.9 mm (17-1/8" x 10-3/4")			
Pixels		1680 x 1050			
Display Colours		16.77 million			
Viewing Angle	Horizontal	178°			
	Vertical	178°			
Brightness		470 cd/m ²			
Contrast Ratio		700: 1			
Response Time (G to G)		6 ms (TYP)			
Horizontal/Vertical	Horizontal	31.469 kHz to 75.000 kHz			
Frequency (PC signals)	Vertical	48 Hz - 65 Hz			
rioquonoy (ro orginalo)	Vortibul	Depending on the signal within the range of these			
		frequencies, some signals may not be displayable in which			
		case, "Out of range " is shown.			
Applicable Standard		3G SDI (Ready) : SMPTE424M/SMPTE425M			
		DUAL LINK HD SDI: SMPTE372M			
		HD SDI: BTA S-004C, SMPTE292M			
		SD SDI: ITU-R BT.656: 525/625, SMPTE259M: 525			
		EMBEDDED AUDIO: SMPTE299M, SMPTE272M			
Audio Output		Internal speaker: 1.0 W + 1.0 W			
Operating Conditions	Operating temperature	5°C to 35°C (41°F to 95°F)			
oportuning containonio	Operating humidity	20% to 80% (non condensing)			
	Storage temperature	-20°C to 60°C			
Power Requirements	Slorage temperature	AC 120/220-240 V,50/60 Hz			
Rated Current		,			
Dimensions (WxHxD)	With desktop stand	1.00 A (AC 120 V) / 0.60 A (AC 220 – 240 V)			
· · · · ·	· · · · · · · · · · · · · · · · · · ·	477 x 394.6 x 243 mm (18-7/8" x 15-5/8" x 9-5/8")			
excluding protrusions)	Without stand	477 x 354 x 99 mm (18-7/8" x 14" x 4")			
Weight	Including stand	10.6 kg (23.3 lbs.)			
	Excluding stand	7.7 kg (16.9 lbs.)			
Provided Accessories		AC power cord, power cord holder x 1,			
		screw x 2 (for power cord holder)			
Input/Output Termina	als				
Video	VIDEO (INPUT 1)	Input/output of composite signal:			
		2 line, BNC connector x 4, 1 V(p-p), 75 Ω			
	VIDEO (INPUT 2)	* The input (IN) and output (OUT) terminals are bridgeconnected (auto termination).			
	DVI-D (HDCP)	DVI-D signal input (compatible with HDCP):			
		DVI-D connector x 1 (compatible with DDC2B)			
	COMPO./RGB	Input/output of analogue component signal/analogue RGB signal			
	(GY, B/PB/B-Y, R/PR/R-Y)	1 line, BNC connector x 6			
		G/Y: 1 V(p-p), 75 Ω (including sync signal)			
		B/P _B /B-Y, R/P _P /R-Y: 0.7 V(p-p), 75 Ω * The input (IN) and output (OUT) terminals are bridgeconnected (auto termination)			
	EXT.SYNC (CS)	Input/output of composite sync signal: 1 line, BNC connector x 2,			
	LA1.0110 (00)	$0.3 V(p-p) - 4 V(p-p), 75 \Omega$ (tri-level sync,			
		negative polarity sync (bi-level), and BB) (including no video signal)			
		I HEYALIVE POIATLY SYTIC (DI-TEVET), ATTA DDT HITCHUITTA TO VIDEO SIGNAT			
		* The input (IN) and output (OUT) terminals are bridgeconnected (auto termination)			
	E. AUDIO HD/SD SDI (IN 1)	The input (N) and output (OUT) terminals are bridgeconnected (auto termination) Digital signal input (compatible with EMBEDDED AUDIO/			
	E. AUDIO HD/SD SDI (IN 1) E. AUDIO HD/SD SDI (IN 2)	The input (IN) and output (OUT) terminals are bridgeconnected (auto termination) Digital signal input (compatible with EMBEDDED AUDIO/ DUAL LINK signals): auto detection, 2 line, BNC connector x 2			
		*The input (N) and output (OUT) terminals are bridgeconnected (auto termination) Digital signal input (compatible with EMBEDDED AUDIO/ DUAL_LINK signals): auto detection, 2 line, BNC connector x 2 Digital signal output (compatible with EMBEDDED AUDIO signals):			
	E. AUDIO HD/SD SDI (IN 2)	The input (IN) and output (OUT) terminals are bridgeconnected (auto termination) Digital signal input (compatible with EMBEDDED AUDIO/ DUAL LINK signals): auto detection, 2 line, BNC connector x 2			
Audio	E. AUDIO HD/SD SDI (IN 2) E. AUDIO HD/SD SDI	*The input (N) and output (OUT) terminals are bridgeconnected (auto termination) Digital signal input (compatible with EMBEDDED AUDIO/ DUAL_LINK signals): auto detection, 2 line, BNC connector x 2 Digital signal output (compatible with EMBEDDED AUDIO signals):			
Audio	E. AUDIO HD/SD SDI (IN 2) E. AUDIO HD/SD SDI (SWITCHED OUT)	* The input (N) and output (UD1) terminals are bridgeconnected (auto termination) Digital signal input (compatible with EMBEDDED AUDIO/ DUAL LINK signals): auto detection, 2 line, BNC connector x 2 Digital signal output (compatible with EMBEDDED AUDIO signals): 1 line switched out, BNC connector x 1			
Audio	E. AUDIO HD/SD SDI (IN 2) E. AUDIO HD/SD SDI (SWITCHED OUT) AUDIO ASSIGN (IN1)	* The input (N) and output (UU) terminals are bridgeconneeted (auto termination) Digital signal input (compatible with EMBEDDED AUDIO/ DUAL LINK signals): auto detection, 2 line, BNC connector x 2 Digital signal output (compatible with EMBEDDED AUDIO signals): 1 line switched out, BNC connector x 1 Analogue audio signal input: 2 line, RCA connector x 4, 500 mV (rms), high impedance			
	E. AUDIO HD/SD SDI (IN 2) E. AUDIO HD/SD SDI (SWITCHED OUT) AUDIO ASSIGN (IN1) AUDIO ASSIGN (IN2)	* The input (N) and output (UU) terminals are bridgeconneeted (auto termination) Digital signal input (compatible with EMBEDDED AUDIO/ DUAL LINK signals): auto detection, 2 line, BNC connector x 2 Digital signal output (compatible with EMBEDDED AUDIO signals): 1 line switched out, BNC connector x 1 Analogue audio signal input: 2 line, RCA connector x 4, 500 mV (rms), high impedance			
Audio External Control	E. AUDIO HD/SD SDI (N 2) E. AUDIO HD/SD SDI (SWITCHED OUT) AUDIO ASSIGN (IN1) AUDIO ASSIGN (IN2) AUDIO ASSIGN (MONITOR OUT)	* The input (N) and output (UU1) terminals are bridgeconnected (aub termination) Digital signal input (compatible with EMBEDDED AUDIO/ DUAL LINK signals): auto detection, 2 line, BNC connector x 2 Digital signal output (compatible with EMBEDDED AUDIO signals): 1 line switched out, BNC connector x 1 Analogue audio signal input: 2 line, RAC connector x 4, 500 mV (rms), high impedance Analogue audio signal output: 1 line, RCA connector x 2, 500 mV (rms)			

Computer Signals

00000 -:-.:::::-----

300 (11 7/8)

51 (2 1/8)

243 (9 <u>5/8)</u>

Specifications



17 (4 5/8)

Þø

* lat the higher position at the lower position Unit: mm (inches)



Front Panel

m

Simulated TV picture E. & O.E. Design and specifications are subject to change without notice.

es may be trademarks or redistered trademarks of their respective owners. Any rights not expressly granted herein are reserved. All company names and product names may be trademarks or registered tradem Copyright © 2010, Victor Company of Japan, Limited (JVC). All Rights Reserved

Printed in Japan ICN-0394

"JVC" is the trademark or registered trademark of Victor Company of Japan, Limited.